On the Parametric Vibrations and Meshless Discretization of Orthotropic Plates with Complex Shape

Jan Awrejcewicz,

*Technical University of Łódź, Department of Automatics and Biomechanics, 1/15
Stefanowski St., 90-924 Łódź, POLAND; awrejcew@p.lodz.pl*

Lidiya Kurpa and Olga Mazur

*The Kharkov State Technical University, Department of Applied Mathematics,
UKRAINE; Kurpa@kpi.kharkov.ua and OlgaMazur@ukr.net*

Abstract

The parametric vibrations of orthotropic plates with complex forms for different types of boundary conditions are studied. The proposed novel hybrid approach is based on combination of the so called R-functions method and the variation method. In particular, advantages of a multimode approximation used for plate behavior analysis are addressed, among others.

Keywords: R-functions method, parametric vibrations, orthotropic plates, Ritz method, Bubnov-Galerkin method.

Introduction

It is clear that problems of plate (shell) vibrations have attracted the attention of scientists and engineers for many years, due to their wide application as components of modern constructions used in civil, aerospace, ship and transport engineering during construction of the so called slender structures including pipelines, bridges, telescopes, submarines, oil-tankers, high-rise buildings, shuttles, rotorcrafts, space stations, military and civil aircrafts, etc. (see, for example recently published monograph and references therein [14]). Plates and shells are also often used in applications in various measuring devices and nano-technology, and they may have very complicated geometry as well as mixed and non-classical boundary conditions. For this reason research of plate behavior with complex form (non-canonical) has received particular interest in many already mentioned application-oriented problems. However, in general, getting reliable solutions to the real dynamical behavior of complex shape plates is in many cases restricted by a

series of mathematical difficulties. In spite of that, for 50 years the R-functions method has been successfully applied to solve linear and nonlinear vibration problems of isotropic, orthotropic and composite plates and shells, including free and forced vibration, static and dynamical stability problems, bifurcation analysis, etc.; however, this powerful method still seems to be ignored by many Western-oriented researchers.

In general, the R-functions allow the basis function to be built in an analytical way for different static and dynamic boundary conditions and on arbitrary domains. Direct application of the classical approaches via FEM (Finite Element Method) or FDM (Finite Difference Method) meets serious difficulties in getting reliable solutions in the case of complex shape domains, but the R-functions approaches allow these problems to be easily overcome and to obtain meshless discretization of bi- and three-dimensional domains of complex plate shapes.

Owing to limitation of space in our paper we encourage readers to be acquainted with a

review of the R-functions theory reported in references [7, 11, 12].

It should be noted that although the R-functions method is not widely known among Western scientists, in the monograph of Amabili [1] a chapter devoted to meshless discretization of plates and shells of complex shape via the R-functions approach is appeared. In this monograph and in paper [9] the R-functions theory was applied to investigation of the nonlinear vibrations of the isotropic shallow shells using one-mode approximation in time.

Parametrically excited vibrations have been investigated in fundamental works [6, 13], and many others. In recent papers [3, 4, 16], new problems of parametric plates (shells) vibrations including their bifurcation and chaotic dynamics are studied. However, in all of these and other works mainly dynamics of rectangular and circular plates with limited (classical) types of boundary conditions have been investigated. In papers [5, 8] instability domain and response curves in instability zones of isotropic plate with complex form are investigated with using of RFM (R-Functions Method) and one-mode approximation.

In this work we propose to use RFM together with multimode approximation for parametric regular and chaotic vibrations analysis of orthotropic plates with complex shape.

The main idea of the proposed method applied by us relies on reduction of the equations governing dynamics of plates to a set of evolutionary ordinary differential equations (ODEs) through an application of variation-type methods. Note that the coefficients of the mentioned ODEs are found by the Ritz method in result of solving a series of linear boundary value problems. On the other hand a set of basic functions is constructed using RFM. It should be emphasized that basic functions build in such way *exactly satisfy boundary conditions*, and therefore the proposed novel method is challenging and preferable than others existing methods devoted to study nonlinear dynamics of plates in a domain of the complex shape.

1. Problem formulation

Let us consider parametric vibrations of an orthotropic plate with constant thickness h subjected to in-plane periodic load p . The equations of the plate dynamics in a mixed form based on the Kirchhoff's hypotheses can be cast in the following form (see [2, 15])

$$L_1 \Phi = -C_1 L(w, w), \quad (1)$$

$$L_2 w = L(w, \Phi) - \varepsilon \frac{\partial w}{\partial t} - \frac{\partial^2 w}{\partial t^2}, \quad (2)$$

where w is deflection of the plate, $\Phi(x, y)$ is the stress (Airy's) function being introduced by the stresses σ_x , σ_y and τ through the standard formulas

$$\frac{\partial^2 \Phi}{\partial y^2} = \sigma_x, \quad \frac{\partial^2 \Phi}{\partial x^2} = \sigma_y, \quad -\frac{\partial^2 \Phi}{\partial x \partial y} = \tau.$$

The operators L_1 , L_2 occurring in (1), (2) are defined as follows

$$L_1 = C_1 \frac{\partial}{\partial x^4} - \left(2\mu_1 - \frac{E_1}{G} \right) \frac{\partial}{\partial x^2 \partial y^2} + \frac{\partial}{\partial y^4}, \quad (3)$$

$$L_2 = \frac{1}{12(1 - \mu_1 \mu_2)} \left(C_1 \frac{\partial^4}{\partial x^4} + \frac{\partial^4}{\partial y^4} + 2(C_3 + C_2) \frac{\partial^4}{\partial x^2 \partial y^2} \right), \quad (4)$$

and the expressions for $L(w, w)$, $L(w, \Phi)$ are

$$L(w, w) = 2 \left(\frac{\partial^2 w}{\partial x^2} \frac{\partial^2 w}{\partial y^2} - \left(\frac{\partial^2 w}{\partial x \partial y} \right)^2 \right),$$

$$L(w, \Phi) = \frac{\partial^2 w}{\partial x^2} \frac{\partial^2 \Phi}{\partial y^2} + \frac{\partial^2 w}{\partial y^2} \frac{\partial^2 \Phi}{\partial x^2} - 2 \frac{\partial^2 w}{\partial x \partial y} \frac{\partial^2 \Phi}{\partial x \partial y}$$

Note that equations (1), (2) are already presented in a non-dimensional form, and relations between dimensional and non-dimensional values are defined as

$$\bar{x} = \frac{x}{a}, \bar{y} = \frac{y}{a}, \bar{w} = \frac{w}{h}, \bar{p} = \frac{a^2 p}{h^3 E_2},$$

$$\bar{t} = \frac{h}{a^2} \sqrt{\frac{E_2}{\rho}} t, \bar{\varepsilon} = \frac{a^2}{h} \sqrt{\frac{\rho}{E_2}} \varepsilon, \bar{\Phi} = \frac{\Phi}{h^2 E_2}.$$

Later, bars over non-dimensional values will be omitted. The coefficients C_1 , C_2 and C_3 appearing in (1)-(4) are defined by the following relations

$$C_1 = \frac{E_1}{E_2}, C_2 = \frac{G(1 - \mu_1 \mu_2)}{E_2},$$

$$C_3 = \frac{G(1 - \mu_1 \mu_2)}{E_2} + \mu_1. \quad (5)$$

In (1)-(5) E_1 , E_2 are elasticity (Young) modules, μ_1 , μ_2 are Poisson's ratios, G is shear modulus, ρ is the plate density, and ε is a damping coefficient.

The evolutionary PDEs are supplemented with initial and corresponding boundary conditions. Initial conditions for plate deflection are taken in the form

$$w|_{t=0} = w_0, w_t|_{t=0} = 0,$$

whereas the boundary conditions are introduced in various ways and they depend on plate type of support.

2. Method of solution

Let us present the plate deflection in the following form

$$w(x, y, t) = \sum_{i=1}^n f_i(t) w_i(x, y). \quad (6)$$

Here w_i are eigenfunctions of a linear vibrations problem of the associated unloaded plate. Thus, the linear problem is reduced to solving the equation

$$L_2 W(x, y) = \omega_L^2 W(x, y), \quad (7)$$

where ω_L is eigenfrequency corresponding to w_i mode of plate vibration. In what follows the problem (7) is further solved by the Ritz

method in combination with R-function theory (this task will be addressed further).

The stress functions are sought for in the following form

$$\Phi(x, y, t) = p\Phi_0 + \sum_{i,j=1}^n f_i(t) f_j(t) \Phi_{ij}(x, y). \quad (8)$$

Here the function $\Phi_0(x, y)$ is solution to the equation

$$L_1 \Phi_0 = 0, \quad (9)$$

which satisfies conditions of the form

$$\frac{\partial^2 \Phi_0}{\partial \tau^2} = -1, \frac{\partial^2 \Phi_0}{\partial n \partial \tau} = 0 \quad (10)$$

on the loaded part of the border. The boundary conditions on the unloaded part of the border depend on support edge.

The functions $\Phi_{ij}(x, y)$ appearing in (8) are solutions to the following equations

$$L_1 \Phi_{ij} = -\frac{1}{2} C_1 L(w_i, w_j). \quad (11)$$

The right hand-side of (11) has the following form

$$L(w_i, w_j) =$$

$$\frac{\partial^2 w_i}{\partial x^2} \frac{\partial^2 w_j}{\partial y^2} + \frac{\partial^2 w_j}{\partial x^2} \frac{\partial^2 w_i}{\partial y^2} - 2 \frac{\partial^2 w_i}{\partial x \partial y} \frac{\partial^2 w_j}{\partial x \partial y}.$$

The boundary conditions for functions Φ_{ij} are homogeneous and defined by corresponding conditions for Φ_0 . In order to solve the problems (9), (10) and (11) for plates with complex shape the matched method including the Ritz approach as well as the R-function theory is used.

Substituting formulas (6) and (8) for w and Φ into equation (2), and applying the standard Bubnov-Galerkin method, we can reduce the input system of nonlinear partial differential equations (PDEs) to an appropriate system of ordinary differential equations (ODEs) of the following form

$$f_m'' + \varepsilon f_m' + \omega_{L,m}^2 f_m - p \sum_{i=1}^n \alpha_i^{(m)} f_i + \sum_{i,j,k=1}^n \beta_{ijk}^{(m)} f_i f_j f_k = 0$$

$$m = 1, \dots, n. \quad (12)$$

Note that the coefficients of the system (12) are defined through double integrals over the investigated domain by the following formulas

$$\alpha_i^{(m)} = \frac{1}{\|w_m\|^2} \iint_{\Omega} L(w_i, \Phi_0) w_m dx dy$$

$$\beta_{ijk}^{(m)} = -\frac{1}{\|w_m\|^2} \iint_{\Omega} L(w_k, \Phi_{ij}) w_m dx dy. \quad (13)$$

System (12) may be also presented in the matrix form

$$\mathbf{f}'' + \varepsilon \mathbf{f}' + (\mathbf{C} - p\mathbf{A})\mathbf{f} + \mathbf{B}(\mathbf{f}) = 0, \quad (14)$$

where

$$\mathbf{A} = \begin{pmatrix} a_1^{(1)} & a_2^{(1)} & \dots & a_n^{(1)} \\ a_1^{(2)} & a_2^{(2)} & \dots & a_n^{(2)} \\ \dots & \dots & \dots & \dots \\ a_1^{(n)} & a_2^{(n)} & \dots & a_n^{(n)} \end{pmatrix}$$

$$\mathbf{C} = \begin{pmatrix} \omega_{L,1}^2 & 0 & \dots & 0 \\ 0 & \omega_{L,2}^2 & \dots & 0 \\ 0 & 0 & \dots & 0 \\ 0 & 0 & \dots & \omega_{L,n}^2 \end{pmatrix}, \mathbf{f} = \begin{pmatrix} f_1 \\ f_2 \\ \dots \\ f_n \end{pmatrix},$$

$$\mathbf{f}' = \begin{pmatrix} f_1' \\ f_2' \\ \dots \\ f_n' \end{pmatrix}, \mathbf{f}'' = \begin{pmatrix} f_1'' \\ f_2'' \\ \dots \\ f_n'' \end{pmatrix},$$

and the vector $\mathbf{B}(\mathbf{f})$ have the following components

$$b_m = \sum_{i,j,k=1}^n \beta_{ijk}^{(m)} f_i f_j f_k.$$

If the investigated plate is in a homogeneous subcritical state and is loaded along the boundary interval parallel to the axis OY (see Figure 3), then the function Φ_0 is yielded by the following simple formula

$$\Phi_0 = -\frac{y^2}{2}. \quad (15)$$

In this case the formula (13) for $\alpha_i^{(m)}$ is essentially simplified, i.e. it takes the form

$$\alpha_i^{(m)} = \frac{1}{\|w_m\|^2} \iint_{\Omega} \frac{\partial^2 w_i}{\partial x^2} w_m dx dy,$$

and hence in this case the problem of finding a solution to the problem (9), (10) can be omitted.

3. R-functions method versus parametric vibrations of the orthotropic plates. The R-functions method is often referred as a *structural method* because the main concept of this method relies on definition of the solution structure of the boundary value problems. This definition was initially given by V.L. Rvachev, who is a precursor and an introducer of the R-functions theory [11].

Let $X(\Omega)$ be a domain of definition of the operator A of the boundary value problem. Suppose that the following boundary conditions are introduced

$$L_k \bar{U} = 0, \quad (k = 1, 2, \dots, q). \quad (16)$$

Definition. A formula $\bar{U} = B(\bar{\Phi}, \omega, \omega_i)$ is called *solution structure* satisfying the boundary conditions (16) and determined on M if for any $\bar{\Phi} \in M$ the identity $L_k B(\bar{\Phi}, \omega, \omega_i) = 0, \quad k = 1, 2, \dots, q$ holds true.

In the above formula B is the operator of solution structure, $\bar{\Phi} = (\Phi_1, \Phi_2, \dots, \Phi_s)$ is the element of some set M , and $B: M \rightarrow X(\Omega)$. In the given case the operator B of the structure solution will be linear one, ω, ω_i are some functions describing equation of a whole boundary domain $\partial\Omega$ and its separated parts $\partial\Omega_i$.

The structure satisfying all boundary conditions is called *general structure* of

solution (GSS). If the constructed solution structure satisfies some of the given boundary conditions then it is called *partial structure solution*. From definition of the solution structure, satisfying some or all boundary condition it follows that element $\bar{\Phi} \in M$, included in structure, may be chosen by an arbitrary way, since the given boundary conditions will be satisfied independently by the mentioned choice. That is why the component is called *indefinite* one. It is natural motivation that this element should be chosen in such a manner that the governing differential equations will be satisfied in the most suitable way.

However, one of the key aspects of the proposed approach is that the constructed solution structure must be completed.

Definition. The *structure solution* satisfying a given boundary condition is called *complete* if there exists such element $\bar{\Phi}^* \in M$ that formula $\bar{U}^* = B(\bar{\Phi}^*, \omega, \omega_i)$ determines the exact solution of the problem.

Definition. The *structure solution* $\bar{U} = B(\bar{\Phi}, \omega, \omega_i)$, $\bar{\Phi} \in M$ is called complete in the sense of the metric $\rho(u, v)$ (or in the sense of the norm $\|\cdot\|_A$) if $\forall \varepsilon > 0 \exists \bar{\Phi}_\varepsilon \in M$, $\rho(\bar{U}_0, B(\bar{\Phi}_\varepsilon, \omega, \omega_i)) < \varepsilon$ (or $\|\bar{U}_0 - B(\bar{\Phi}_\varepsilon, \omega, \omega_i)\|_A < \varepsilon$), where $\bar{U}_0$ is a classical (or generalized) solution of the problem.

Note that only complete structures are interesting for applications, and for the problems of plate's theory some of such structures had been already constructed and reported in references [7, 11, 12].

The previous discussions related to solutions structure allows to conclude that their construction is possible assuming knowledge of equations the whole plate boundary, and also one may construct the analytical expressions of the plate boundary parts. The method of construction equations of a domain boundary as well as of its any part was also proposed by V.L. Rvachev [11]. As it had been shown in his numerous works first it is needed to construct the so-called logic formula of the domain, also

named two-valued predicate, which is defined as follows

$$\Omega = \Omega(M) = \begin{cases} 0, & \forall M \notin \Omega, \\ 1, & \forall M \in \Omega. \end{cases}$$

Usually, the general predicate is build with a help of the corresponding predicates $\Omega_i(M)$ of the sub-domains forming the given domain. In other words the general predicate is a Boolean function $F(\Omega_1, \Omega_2, \dots, \Omega_n)$. The function F can be complete one depending on its arguments $\Omega_1, \Omega_2, \dots, \Omega_n$, which are also Boolean variables. That function is obtained by applying the standard Boolean operations $\vee, \wedge, -$ (disjunction, conjunction and negation, respectively) corresponding to the union $\cup$, intersection $\cap$ and negation of the applied sets. In order to give an insight to the illustrated method let us construct the logic formula for the domain shown in Figure 1.

Fig. 1: A T-shaped plate

This domain consists of the following sub-domains:

$$\Omega_1 = \left(f_1 = \frac{1}{a} \left(\left(\frac{a}{2} \right)^2 - x^2 \right) \geq 0 \right) \text{ is a vertical}$$

band bounded by straight lines $x = \pm \frac{a}{2}$; (17)

$$\Omega_2 = \left(f_2 = \frac{1}{b} \left(\left(\frac{b}{2} \right)^2 - y^2 \right) \geq 0 \right) \text{ is a horizontal}$$

strip bounded by straight lines $y = \pm \frac{b}{2}$; (18)

$$\Omega_3 = \left(f_3 = \frac{1}{c} \left(\left(\frac{c}{2} \right)^2 - x^2 \right) \geq 0 \right) \text{ is a vertical}$$

strip bounded by straight lines $x = \pm \frac{c}{2}$;

$\Omega_4 = (f_4 = y - g \geq 0)$ is a half-plane located above the line $y = g$;

The predicate of the given domain is defined by the following formula

$$\Omega = (\Omega_1 \wedge \Omega_2) \wedge (\Omega_3 \vee \Omega_4).$$

In order to construct the equation of the domain boundary in an analytical form we can apply the theorem proved by V.L.Rvachev, accordingly to which it is sufficient to perform a formal replacement of the characteristic functions Ω_i by continuous functions f_i and Boolean operators $\vee, \wedge, -$ by the corresponding R-operations $\vee_\alpha, \wedge_\alpha, -$ (R-disjunction, R-conjunction, R-negation). These R-operations are defined as follows;

$$x \vee_\alpha y = \frac{1}{1+\alpha} \left(x + y + \sqrt{x^2 + y^2 - 2\alpha xy} \right)$$

$$x \wedge_\alpha y = \frac{1}{1+\alpha} \left(x + y - \sqrt{x^2 + y^2 - 2\alpha xy} \right),$$

$$\bar{x} = -x.$$

Here the parameter α is any number from interval $(-1, 1]$.

Thus, if the value α will be taken equal to zero, then the equation $\omega(x, y) = 0$ of the whole domain boundary may be presented as follows:

$$\omega(x, y) = (f_1 \wedge_0 f_2) \wedge_0 (f_3 \vee_0 f_4). \quad (19)$$

It should be noted that R-functions theory allows constructing the equation of the border which is described by function $\omega(x, y)$ normalized up 1st order. In this case the function $\omega(x, y)$ satisfies the following conditions

$$\begin{aligned} \omega &= 0, \quad \frac{\partial \omega}{\partial n} = 1, \quad \forall (x, y) \in \partial\Omega, \\ \omega &> 0, \quad \forall (x, y) \in \Omega. \end{aligned}$$

Note that function $\omega(x, y)$ defined by equation (19) will be normalized up 1st order due to normalization of the constituent functions $f_i, (i = \overline{1, 4})$.

Sometimes it is necessary to construct the function $\omega^{(2)}(x, y)$ which is normalized up 2nd order, that is, such a function as to satisfy conditions

$$\omega^{(2)} = 0, \quad \frac{\partial \omega^{(2)}}{\partial n} = 1, \quad \frac{\partial^2 \omega^{(2)}}{\partial n^2} = 0$$

$$\forall (x, y) \in \partial\Omega, \quad \omega^{(2)} > 0, \quad \forall (x, y) \in \Omega.$$

As shown in [11] in order to construct the function $\omega^{(2)}(x, y)$ normalized up 2nd order with help of function $\omega(x, y)$ normalized up 1st order the following formula may be applied

$$\omega^{(2)} = \omega(x, y) + \frac{1}{3} \omega(x + h_1, y + h_2).$$

The functions $h_1(x, y), h_2(x, y)$ are defined as

$$h_1 = -\omega \left(x + \frac{1}{2} \omega(x, y), y \right) +$$

$$\omega \left(x - \frac{1}{2} \omega(x, y), y \right),$$

$$h_2 = -\omega \left(x, y + \frac{1}{2} \omega(x, y) \right) +$$

$$\omega \left(x, y - \frac{1}{2} \omega(x, y) \right).$$

Let us consider some type of the boundary conditions and construct the corresponding solutions structures for plates of the complex shape but bounded by straight lines (Figure 1 and Figure 3).

Suppose that the plate is simply supported along all counters. In this case the boundary conditions for eigenfunctions w_i are

$$w_i = 0, \frac{\partial^2 w_i}{\partial n^2} = 0, (x, y) \in \partial\Omega. \quad (20)$$

Applying R-functions theory it is possible to prove that solution structure satisfying all boundary conditions (20) for w_i has the following form:

a) differential structure

$$w_i = \omega P_1 - \frac{\omega^2}{2} (2D_1 P_1 + P_1 D_2 \omega), \quad (22)$$

b) differential-difference structure

$$w_i = \omega^{(2)} P_1 + \omega (h_1 P_{1,x} + h_2 P_{1,y}). \quad (23)$$

Here differential operators D_1 and D_2 have been defined by the formulas [7, 11, 12]:

$$D_1 P_1 = \frac{\partial \omega}{\partial x} \frac{\partial P_1}{\partial x} + \frac{\partial \omega}{\partial y} \frac{\partial P_1}{\partial y},$$

$$D_2 \omega = \left(\frac{\partial \omega}{\partial x} \right)^2 \frac{\partial^2 \omega}{\partial x^2} + 2 \frac{\partial \omega}{\partial x} \frac{\partial \omega}{\partial y} \frac{\partial^2 \omega}{\partial x \partial y} + \left(\frac{\partial \omega}{\partial y} \right)^2 \frac{\partial^2 \omega}{\partial y^2},$$

and on domain boundary coincides with normal derivatives

$$D_1 P_1|_{\partial\Omega} = \frac{\partial P_1}{\partial n}, \quad D_2 \omega|_{\partial\Omega} = \frac{\partial^2 \omega}{\partial n^2}.$$

In the above n is interior normal to domain boundary. In differential-difference structure (23) comma means derivatives with respect to x and y .

Let us consider the mixed boundary conditions for deflection function. Suppose that eigenfunctions w_i have to satisfy the following conditions

$$w_i = 0, \frac{\partial^2 w_i}{\partial n^2} = 0, (x, y) \in \partial\Omega_1,$$

$$w_i = 0, \frac{\partial w_i}{\partial n} = 0, (x, y) \in \partial\Omega_2.$$

In order to construct the solution structure satisfying current mixed boundary conditions

let us apply the generalize formula by Lagrange [11]. Two kind of formulas are presented below:

a) differential structure

$$w_i = \frac{\omega_1^2}{\omega_1^3 + \omega_2^2} \left(\omega_1 P_1 - \frac{\omega_1^2}{2} (2D_1 P_1 + P_1 D_2 \omega_1) + \omega_1^3 P_2 \right) \quad (24)$$

b) differential-difference structure

$$w_i = \frac{\omega_2^2}{\omega_1^3 + \omega_2^2} \left(\omega_1^{(2)} P_1 + \omega_1 (h_1 P_{1,x} + h_2 P_{1,y}) + \omega_1^3 P_2 \right). \quad (25)$$

In (24), (25) $\omega_1(x, y) = 0, \omega_2(x, y) = 0$ are equations of the clamped and simply-supported parts of boundary, respectively.

The form of the presented structures for considered conditions is more complicated if the boundary is a curved one [7, 11, 12]. However, it is needed to satisfy only main boundary conditions, then these structures are simplified essentially and takes the form:

for simply supported plate:

$$w_i = \omega \cdot P_1, \quad (26)$$

for mixed conditions:

$$w_i = \omega \cdot \omega_1 \cdot P_1. \quad (27)$$

Note that in (22)-(27) P_1, P_2 are indefinite components of the structure that is presented as an expansion in a series of some complete system (power polynomials, Tchebyshev polynomials, splines, etc.).

More details about solution structures satisfying boundary conditions for stress function Φ one may find in [7, 11, 12]. Later we will present structures for considered problems.

4. Numerical results.

4.1. Testing problem

In order to test and validate the proposed approach let us investigate the parametric vibrations of the rectangular simply supported

plate (Figure 2) excited longitudinally by $p = p_0(1 - \sin \theta t)$.

Fig. 2: A rectangular plate

$$I(W) = \iint_{\Omega} \left(C_1 \left(\frac{\partial^2 W}{\partial x^2} \right)^2 + 2C_1\mu_2 \frac{\partial^2 W}{\partial x^2} \frac{\partial^2 W}{\partial y^2} + \left(\frac{\partial^2 W}{\partial y^2} \right)^2 + 4C_2 \left(\frac{\partial^2 W}{\partial x \partial y} \right)^2 - \lambda^2 W^2 \right) d\Omega$$

where $\lambda^2 = 12 \cdot (1 - \mu_1 \mu_2) \omega_L^2$. The series of basic functions, which satisfy boundary conditions, is constructed by the R-function method. For conditions (28) a structure of solution (26) satisfying only main conditions is applied. Indefinite component P_1 in (26) is presented through expansion into series

$$P_1 = \sum_{k=1}^l a_k \varphi_k^{(1)}. \quad (30)$$

In (30) factors a_k are indefinite ones which are founded from condition of functional

$$I(\Phi_{ij}) = \iint_{\Omega} \left[C_1 \left(\frac{\partial^2 \Phi_{ij}}{\partial x^2} \right)^2 + \frac{E_1}{G} \frac{\partial^2 \Phi_{ij}}{\partial x^2} \frac{\partial^2 \Phi_{ij}}{\partial y^2} + \left(\frac{\partial^2 \Phi_{ij}}{\partial y^2} \right)^2 - 2\mu_1 \left(\frac{\partial^2 \Phi_{ij}}{\partial x \partial y} \right)^2 + L(w_i, w_j) \Phi_{ij} \right] d\Omega.$$

The structure of solutions for functions Φ_{ij} , which satisfy the boundary conditions (29) are constructed in the form

$$\Phi_{ij} = \omega \cdot P_3. \quad (31)$$

Boundary conditions are considered in the form

$$w = 0, \quad \frac{\partial^2 w}{\partial n^2} = 0, \quad (28)$$

$$\Phi = 0, \quad \frac{\partial^2 \Phi}{\partial n^2} = 0, \quad (x, y) \in \partial\Omega. \quad (29)$$

As stated above, eigenfunctions w_i and eigenfrequencies $\omega_{L,i}$ are found by the Ritz method. The corresponding functional has the following form [10]

stationarity, $\{\varphi_k^{(1)}\}$ is some complete system of functions, taken in the given work as power polynomials.

Note that for rectangular plate function Φ_0 may be taken in the form (15). Now let us find the functions $\Phi_{ij}(x, y)$. To solve the problem (11) with boundary conditions (29) the Ritz method together with RFM are used also. One may easily prove that the variational statement of the problem is reduced to minimization of the following functional [10]

The function $\omega(x, y)$ in (26), (31) normalized up 1st for rectangular plate can be written as follows

$$\omega = f_1 \cdot f_2 / (f_1 + f_2)$$

or with the help of the R-functions

$$\omega = f_1 \wedge_0 f_2,$$

where f_1, f_2 are defined by (17), (18).

The indefinite component P_3 in (31) is expanded into a series similarly to P_1 in (30). By the symmetry of the boundary value problem for approximation of indefinite components P_1, P_3 in (26), (31) the following power polynomials are used:

$$1, x^2, y^2, x^4, x^2 y^2, y^4, \dots$$

Control of results convergence allows the use of twenty one basic functions, which corresponds to tenth power of polynomials. System (14) is integrated by the standard fourth-order Runge-Kutta method.

Calculations are carried out for fixed value of exciting frequency $\theta = 8$ and with variations of p_0 (the values of p_0 are chosen the same as in [3] for a validation purpose). Values of

geometrical parameters, damping coefficient and initial amplitude are the following ones: $a/b=1, \varepsilon=1, w_0=0.001$. During our study one-order and three-order approximations are applied, and since the rectangular plate is symmetrical to the axes OX and OY , respectively, the modes (1,1), (3,1), (1,3) (Table 1) are applied.

Analysis of dynamic behavior is carried out at the point of maximum deflection of the first form $M(x_0, y_0)$:

$$w(x_0, y_0, t) = \sum_{i=1}^3 w_i(x_0, y_0) f_i(t). \quad (32)$$

For square plate maximum point of first form is the plate central point $M(0,0)$ (in Table 2 dependences $w(t)$ and $\dot{w}(w)$ are presented).

Table 1. Modes of vibrations and corresponding values of non-dimensional frequencies $\Lambda_i = \omega_{L,i} a^2 (\rho / E_2 h^2)^{1/2}$ for the square simply supported plate

$\Lambda_1 = 5.975$	$\Lambda_2 = 29.867$	$\Lambda_3 = 29.875$

Comparison of the obtained results with that of reference [3] allows drawing a conclusion that one-mode approximation is insufficient in getting reliable results. However, the results obtained via third-modes approximation are in a good agreement with the results reported in reference [3]. Note that we approximated the displacements of the rectangular plate by truncated series with number of terms not more than fifteen.

4.2 Parametric vibrations of plate with complex shape.

Example 1. In what follows we also illustrate our approach using an example of a complex shape plate, namely the plate with a rectangular cut-out (Figure 3). Let us suppose the plate is loaded longitudinally along the edges parallel to axis OY . Sections of boundary corresponding to cut-outs are clamped; other part of the plate boundary is simply supported. In other words the considered boundary conditions are defined in the following form

Table 2. Effects of the number modes on the time history $w(t)$ and phase portrait $\dot{w}(w)$ for the square simply supported plate

$$w = 0, \quad \frac{\partial w}{\partial n} = 0, \quad (x, y) \in \partial\Omega_1$$

$$(\Omega_1 : x \in \left[c, \frac{a}{2} \right], y = g; x = c, y \in \left[g, \frac{b}{2} \right])$$

$$w = 0, \quad \frac{\partial^2 w}{\partial n^2} = 0, \quad (x, y) \in \partial\Omega_2 = \partial\Omega / \partial\Omega_1, \quad (33)$$

$$\frac{\partial^2 \Phi}{\partial \tau^2} = 0, \quad \frac{\partial^2 \Phi}{\partial n \partial \tau} = 0, \quad (x, y) \in \partial\Omega. \quad (34)$$

The computations are carried out for an isotropic plate. The following harmonic loading is taken

$$p = p_0 \sin \theta t, \quad (35)$$

and the fixed value of excited frequency θ taken close to the eigenfrequency and control parameter p_0 ($b/a = 1, \varepsilon = 1, w_0 = 0.001$).

Fig. 3: A rectangular cut-out plate

For the given conditions (33) the structure of solution for deflection w satisfying only the main boundary conditions are taken in the form (27), where $\omega(x, y) = 0$ is equation of the whole boundary domain, $\omega_1(x, y) = 0$ is equation of the clamped part of the boundary. The functions $\omega(x, y)$ and $\omega_1(x, y)$ are defined as follows

$$\omega(x, y) = (f_1 \wedge_0 f_2) \wedge_0 (f_3 \vee_0 f_4)$$

$$\omega_1(x, y) = f_3 \vee_0 f_4.$$

The functions f_1, f_2 are defined by (17), (18), and the functions f_3, f_4 have the following form

$$f_3 = g - y \geq 0, \quad f_4 = c - x \geq 0.$$

Since the plate under consideration has a homogeneous subcritical state, the task of finding function Φ_0 is omitted.

The algorithm already described and illustrated for the square plate analysis is applied for finding functions Φ_{ij} . It is clear that boundary conditions (34) for functions Φ_{ij} may be replaced by conditions

$$\Phi_{ij} = 0, \quad \frac{\partial \Phi_{ij}}{\partial n} = 0.$$

The structure of the solution used for these conditions has the form

$$\Phi_{ij} = \omega^2 \cdot P_3. \quad (36)$$

Indefinite components P_1, P_3 in (27), (36) are approximated by the following power polynomials

$$1, x, y, x^2, xy, y^2, x^3, x^2y, xy^2, y^3, \dots$$

To verify the obtained results let us investigate the convergence of the natural frequencies increasing number of the series terms and applying the different solution structures. Table 3 shows the values of the non-dimensional frequencies for plate with fixed ratio $c/a = g/a = 0.2, b/a = 1$.

Table 3. Convergence of non-dimensional frequencies $\Lambda_i = \omega_{L,i} a^2 (\rho / Eh^2)^{1/2}$ for isotropic rectangular cut-out plate in increasing number n of basic functions for deflection $w(x, y)$ (Fig 3, $b/a = 1, c/a = g/a = 0.2$)

n	Structure (26)			Structure (24)		
	Λ_1	Λ_2	Λ_3	Λ_1	Λ_2	Λ_3
21	9.039	16.626	21.637	9.484	16.559	22.290
28	9.018	16.408	21.168	9.274	16.285	21.224
36	9.016	16.161	21.156	9.190	16.002	21.147
45	9.014	16.080	21.039	9.132	15.936	21.053
55	9.014	16.036	21.017	9.099	15.885	21.010
66	9.012	16.010	20.994	9.084	15.862	20.983
78	9.011	15.980	20.981	9.063	15.842	20.961
91	9.010	15.959	20.968	9.046	15.827	20.940
105	9.009	15.949	20.961	9.036	15.817	20.918

As follows from Table 3, the linear frequencies converge within three significant digits starting from 45 terms of series for structure (26) and from 66 terms of the series for structure (24). Therefore 45 basic functions are used for further calculations. Difference of the results obtained with help of different structures does not exceed 0.8% that confirms their validation.

One of the ways for examination of the obtained results is degeneration of the complex domain in canonical one. For example, if we will increase the ratio c/a and g/a then given plate takes the square shape, for which the natural frequency are known. Indeed, Table 4 shows that the natural frequencies approach the corresponding values for square plate when c/a and g/a approach value equal to 0.5.

Table 4. Effects of plate aspect cut-out ratio c/a and g/a on non-dimensional frequencies $\Lambda_i = \omega_{L,i} a^2 (\rho / E h^2)^{1/2}$ of the rectangular cut-out plate with mixed boundary conditions (Fig.3, $b/a = 1$)

$c/a = g/a$	Λ_1	Λ_2	Λ_3
0.2	9.014	16.080	21.039
0.3	7.272	15.159	18.198
0.4	6.312	14.954	15.927
0.45	6.063	14.940	15.213
0.48	5.995	14.938	15.001
Square plate[15]	5.973	14.933	14.933

Observe that our so far investigated plate possesses an asymmetric shape. Further we will take into account the first three vibration modes. These modes are presented in Table 5.

Table 5. Modes of vibrations and corresponding values of non-dimensional frequencies

$\Lambda_i = \omega_{L,i} a^2 (\rho / E_2 h^2)^{1/2}$ for the rectangular cut-out plate with mixed boundary conditions (Fig 3, $b/a = 1$ $c/a = g/a = 0.2$)

$\Lambda_1 = 9.014$	$\Lambda_2 = 16.080$	$\Lambda_3 = 21.039$

One- and three-modes approximations are applied to obtain the results for excited frequency $\theta = 9$. Time history $w(t)$ and phase portrait $\dot{w}(w)$ at the point of the first mode

maximum (32) are shown in Table 6 (the studied plate achieves its maximum deflection in point $M(-0.104a, -0.104a)$). Further results are obtained for $c/a = g/a = 0.2$.

Table 6. Effects of the number modes on the time history $w(t)$ and phase portrait $\dot{w}(w)$ for the rectangular cut-out plate with mixed boundary conditions (Fig 3, $b/a = 1$ $c/a = g/a = 0.2$)

	$w(t)$	$\dot{w}(w)$
p_0	One mode approximation	
6.5
14
p_0	Three mode approximation	
6.5
14

The system behavior is similar for one and three mode approximations when $p_0 \in [0, 6]$.

Increasing parameter p_0 results in a qualitative change of the plate vibrations, and a transition from regular to chaotic plate regime is observed assuming that third order approximation is applied. In other words the results obtained using one-order approximation for

$p_0 \in [6.1, 14]$ qualitatively differ from that of three-order approximation.

Example 2. Let us revisit the parametric vibrations of the orthotropic plate of complex shape shown in Figure 1. The plate is subjected to load of the form (35), which is applied longitudinally along the plate edges being parallel to the axis OY . Assume that deflection w satisfies boundary conditions (28), for stress

function Φ boundary conditions have the form (34).

Our numerical results are obtained for material (glass-epoxy) with the following properties

$$E_1 / E_2 = 1, \quad G / E_2 = 0.3846$$

$$\mu_1 = \mu_2 E_1 / E_2 = 0.0833.$$

It should be noted that the current plate is in a homogenous subcritical state, and the function Φ_0 can be presented in the form (15). Structures of solution (26) and (36) for functions w_i and Φ_{ij} are applied respectively. By symmetry of the boundary value problem

for variable x the indefinite components P_1 and P_3 in formulas (26), (36) are approximated by the following power polynomials $1, y, x^2, y^2, x^2 y, y^3, x^2 y, y^3, \dots$

The validation of the obtained results for this plate has been carried out by methods described for plate shown in Figure 3. Table 7 shows the effect of cut-out decrease on non-dimensional natural frequencies. Like in previous example, if sizes of the cut-out are decreasing then frequencies approach corresponding frequencies of square simply supported orthotropic plate.

Table 7. Effects of plate aspect cut-out ratio c/a and $\frac{l}{a} = \frac{g+b/2}{a}$ on non-dimensional frequencies

$\Lambda_i = \omega_{L,i} a^2 (\rho / E_2 h^2)^{1/2}$ of the orthotropic simply supported T-plate
(Fig.1, $b/a=1$, $E_1/E_2=1$, $G/E_2=0.3846$, $\mu_1=\mu_2 E_1/E_2=0.0833$)

$\frac{c}{a}$	$\frac{l}{a} = \frac{g+b/2}{a}$	Λ_1	Λ_2	Λ_3
0.35	0.2	9.365	19.957	33.050
0.4	0.1	8.131	17.095	31.403
0.45	0.05	7.664	16.123	30.432
0.48	0.02	7.553	15.909	30.189
Square plate[2],0.5	0	7.536	15.875	30.150

It should be noted that for square plates the frequencies corresponding to modes (1, 1), (1, 2), (1, 3) will be calculated. Degeneration of plate with complex form in square plate leads to decrease of natural frequencies. For ratio $\frac{c}{a} = 0.5$ and $\frac{l}{a} = \frac{g+b/2}{a} = 0.02$, when the plate under consideration practically degenerates in square one the corresponding frequencies are very close to each other. This fact confirms the reliability of the obtained results.

In order to find w_i and Φ_{ij} forty nine basic functions are used, which corresponds to the 12th power of the associated polynomials. Further results were obtained for $c/a=0.6$,

$g/a=0.1$, $b/a=1$, $\varepsilon=1$, $w_0=0.001$. In Table 8 the first three modes (1,1),(1,2),(1,3) with the corresponding linear frequencies are presented.

In what follows the effect of multimode approximation (three modes) on the investigated plate characteristics is further studied for a fixed value of the excited frequency $\theta=19$ taken near the main eigenfrequency and for various values of the parameter p_0 .

Dependencies $w(t)$ and $\dot{w}(w)$ are computed at the point of first mode maximum $M(0, -0.141a)$, and the obtained results are reported in Table 9.

Table 8. Modes and corresponding values of non-dimensional frequencies $\Lambda_i = \omega_{L,i} a^2 (\rho / E_2 h^2)^{1/2}$ for simply supported orthotropic plate (Fig. 1, $c/a = 0.6$, $g/a = 0.1$, $b/a = 1$)

$\Lambda_1 = 19.373$	$\Lambda_2 = 22.665$	$\Lambda_3 = 37.013$

Table 9. Effects of the number modes on the time history $w(t)$ and phase portrait $\dot{w}(w)$

p_0	One mode approximation	
12.2
21
p_0	Three modes approximation	
12.2
21

On analyzing the data in Table 9 one may see that results obtained with use one-mode approximation differ from results obtained applying three-modes approximation and draw a conclusion that for chaotic behavior of plate investigation one-mode approximation can not be used.

5. Conclusions.

A novel method of parametric regular and chaotic vibrations of orthotropic plates with complex shapes for different types of boundary conditions has been proposed. The proposed method is based on applying a hybrid approach matching both variational methods and R-function theory. It has been shown and illustrated that application of the RFM often requires use of basic functions, and a way of their construction has been outlined. The numerical results are obtained for plates of either square or complex shapes using first and third modes of approximations. In addition to the general theoretical results our numerical analysis has shown that one mode approximation cannot be used in all regimes of nonlinear dynamics of the orthotropic plates, and in particular during their chaotic dynamics.

References

- [1] Amabili M., *Nonlinear Vibrations and Stability of Shells and Plates*. Cambridge University Press, Cambridge, 2008.
- [2] Ambartsumian S.A., *Theory of Anisotropic Plates*. Nauka, Moscow, 1967, in Russian.
- [3] Awrejcewicz J., Krys'ko A.V. *Analysis of complex parametric vibrations of plates and shells using the Bubnov-Galerkin approach*. Applied Mechanics, 73, 2003, 495-504.
- [4] Awrejcewicz J., Krys'ko V.A., Moldenkova T., *Mathematical model of dissipative parametric vibrations of flexible plates with non-homogeneous boundary conditions*. Mathematical Problems in Engineering, 2006, 1-16.
- [5] Awrejcewicz J., Kurpa L., Mazur O., *Research of Stability and Nonlinear vibration of plates by R-Functions Method*, 179-189. In: Awrejcewicz J. (Ed.), *Modeling Simulation and Control of Nonlinear Engineering Dynamical Systems*. Springer-Verlag, Berlin, 2009.
- [6] Bolotin V.V., *The Dynamic Stability of Elastic Systems*. Gos. Tech. Izdat., Moscow, 1956, in Russian.
- [7] Kurpa L.V., *R-functions Method for Solving Linear Problems of Bending and Vibrations of Shallow Shells*. Kharkiv NTU Press, Kharkiv, 2009, in Russian.
- [8] Kurpa L.V., Mazur O.S. *Parametric vibrations of plate with complex shape*. Mashinostroyeniye. 2008, №3 (33), pp. 9-15, in Ukrainian.
- [9] Kurpa L., Pilgun G., Amabili M., *Nonlinear vibrations of shallow shells with complex boundary: R-functions method and experiments*. Journal of Sound and Vibration, 306, 2007, 580-600
- [10] Mikhlin S.G., *Variational Methods in Mathematical Physics*. Nauka, Moscow, 1970, in Russian.
- [11] Rvachev V.L., *Theory of R-functions and Some of Its Applications*. Naukova Dumka, Kiev, 1982, in Russian.
- [12] Rvachev V.L., Kurpa L.V., *The R-functions in Problems of Plates Theory*. Naukova Dumka, Kiev, 1987, in Russian.
- [13] Schmidt G., *Parametric Vibrations*. Mir, Moscow, 1978, in Russian.
- [14] Virgin L.N., *Vibration of Axially Loaded Structures*. Cambridge University Press, Cambridge, 2007.
- [15] Volmir, A.S., *Nonlinear Dynamics of Plates and Shells*. Nauka., Moscow, 1972, in Russian.
- [16] Zhang W., Zhaomiao L. *Global dynamics of a parametrically and externally excited thin plate*. Nonlinear Dynamics, 24, 2001, 245-268.